



# SQYPower

Clean power!



- ✓ ZERO fuel
- ✓ ZERO oil change
- ✓ ZERO oil filter change
- ✓ ZERO noise
- ✓ ZERO emissions
- ✓ Minimal maintenance/service
- ✓ Minimal risk of break down
- ✓ Minimal downtime
- ✓ Very long lifetime
- ✓ Minimal running cost
- ✓ Attractive ROI

## Traditional generators

- Fuel
- Oil change
- Oil filter change
- Frequent service
- Noise
- CO2 Emmissions
- Risk of breakdown





<b>AC input 1 voltage:</b>	230+N+PE+ Vac
<b>AC input 2 voltage:</b>	3x400+N+PE Vac
<b>AC input frequency:</b>	50 Hz
<b>Max AC input current:</b>	16A
<b>Output voltage:</b>	3x400v+N+PE Vac
<b>Output power:</b>	15kVA /12kW @ 25°C
<b>Output peak power:</b>	27kW
<b>Battery type:</b>	Lead acid - 12V 165-200Ah
<b>Battery Capacity:</b>	48V / 165-200Ah
<b>Operation temperature:</b>	-10 to 30°C (Battery capacity will decrease in low temperature)
<b>Protection category:</b>	IP 54
<b>Product weight:</b>	Approx. 380kg
<b>Product dimensions</b>	110x60x90cm



SQYPower 